




## DATA SHEET **8A CONTROLLER FOR 8 ZONE LED REMOTE** SKU: SA-CTRL-8A-RGB



## **Product Description**

Solid Apollo's controller for the 8 Zone LED Remote is now available in 8 amps which means more power for your buck. At 24V DC, you can now power up to a maximum of 192W per channel, a total of 768W of Color Changing RGB LED Strip Lights. This dims smoothly from 0-100%, has a soft on/off feature, and remembers last setting when unplugged or power is lost.

The controller is easy to mount to a variety of hard surfaces and slim enough to hide out of sight. A learning key button easily pairs with RGB-W remotes to work with any LED project. Just one push of the button begins the pairing process. Add as many optional RGB-W controllers as you wish to create up to 8 different control zones. Each zone can have an endless number of controllers which will let you expand any installation from a small size to a colossal project. The 8A Controller for 8 Zone LED Remote is UL Listed ensuring the safety and durability for the lifetime of the unit.

- UL Listed E493882
- LED Wizard RGB Controller 8 Amps
- Controls 4 channels: RGB (Red, Green, Blue) + White
- Perfect for Adding Extra Zones
- Learning Key Button Ensures Quick and Seamless Pairing
- Memory Function Remembers Last Setting Even
  if Power Goes Off
- Soft On/Off
- 12-36V DC Compatible
- 768W@24V DC, 384W@12V DC

## Quick Spec.

• Dimmable:	Yes, by remote	• Warranty:	3 Years	Product Color:	White
• Input Voltage:	12-36V DC	• Weight:	0.4 lb	<ul> <li>Product Material:</li> </ul>	High-Grade Plastic
Max Power:	768W@24VDC	Dimensions:	3.7"x2.3"x1.1"	<ul> <li>Working Temp:</li> </ul>	-4 - 122F
	384W@12VDC	<ul> <li>IP Rating:</li> </ul>	IP33	Certifications:	UL Listed, CE, RoHs
• Max Amp:	8A	<ul> <li>Control System:</li> </ul>	Triac PWM		

## **Technical Diagrams**

